AD-A165 219 STOCHASTIC ESTIMATION IN COMBINED ARMS LANCHESTER MODELING OF WARFARE(U) ARMY MATERIEL SYSTEMS ANALYSIS ACTIVITY ABERDEEN PROVING GROUND MD H E COHEN JUL 85 AMSAA-TR-414 F/G 15/7 1/1 NL

UNCLASSIFIED





MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963-A

AD-A165 219

(12)

AD

AMSAA

TECHNICAL REPORT NO. 414

STOCHASTIC ESTIMATION IN COMBINED ARMS LANCHESTER MODELING OF WARFARE

HERBERT E. COHEN

DTIC
ELECTE
MAR 1 3 1986
S D
B

JULY 1985

DTIC FILE COPY

APPROVED FOR PUBLIC RELEASE; DISTRIBUTION UNLIMITED

U. S. ARMY MATERIEL SYSTEMS ANALYSIS ACTIVITY
ABERDEEN PROVING GROUND, MARYLAND

86 3 13 003

DISPOSITION

Destroy this report when no longer needed. Do not return it to the originator.

DISCLAIMER

The findings in this report are not to be construed as an official Department of the Army position unless so specified by other official documentation.

WARNING

Information and data contained in this document are based on the input available at the time of preparation. The results may be subject to change and should not be construed as representing the DARCOM position unless so specified.

TRADE NAMES

The use of trade names in this report does not constitute an official endorsement or approval of the use of such commercial hardware or software. The report may not be cited for purposes of advertisement.

SECURITY CLASSIFICATION OF THIS PAGE *(When Data Entered)*

REPORT DOCUMENTATION PAGE

READ INSTRUCTIONS BEFORE COMPLETING FORM

1. REPORT NUMBER: Technical Report 414	2. GOVT ACCESSION NO.: ADA165219
3. RECIPIENT'S CATALOG NUMBER:	
4. TITLE *(and Subtitle)*: Stochastic Estimation in Combined Arms Lanchester Modeling of Warfare	5. TYPE OF REPORT & PERIOD COVERED: Technical Report
6. PERFORMING ORG. REPORT NUMBER:	
7. AUTHOR(s): Herbert E. Cohen	8. CONTRACT OR GRANT NUMBER(s):
9. PERFORMING ORGANIZATION NAME AND ADDRESS: Director, US Army Materiel Systems Analysis Activity, ATTN: AMXSY-MP. Aberdeen Proving Ground, MD 21005-5071	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS:
11. CONTROLLING OFFICE NAME AND ADDRESS: Commander, US Army Materiel Command, 5001 Eisenhower Ave. Alexandria, VA 22333-0001	12. REPORT DATE:
	13. NUMBER OF PAGES:
14. MONITORING AGENCY NAME & ADDRESS *(if different from Controlling Office)*:	15. SECURITY CLASS. *(of this report)*: Unclassified
	15a. DECLASSIFICATION/DOWNGRADING SCHEDULE:

16. DISTRIBUTION STATEMENT *(of this Report)*
Approved for public release; distribution is unlimited.

17. DISTRIBUTION STATEMENT *(of the abstract entered in Block 20, if different from Report)*

18. SUPPLEMENTARY NOTES

19. KEY WORDS *(Continue on reverse side if necessary and identify by block number)*
Lanchester Modeling
Combined Arms
Kalman - Bucy Filter
Kalman Filter
Continuous Kalman Filter
Discrete Kalman Filter
Homogeneous Force Model
Heterogeneous Force Model

20. ABSTRACT *(Continue on reverse side if necessary and identify by block number)*
This present paper calls attention to the fact that stochastic estimation theory, as practiced in modern control theory, provides a method for predicting conditions on the battlefield from measurements or observations of the battle area that are themselves uncertain and where the parameters of the mathematical model are not known precisely.

DD FORM 1 JAN 73 1473 EDITION OF 1 NOV 65 IS OBSOLETE

SECURITY CLASSIFICATION OF THIS PAGE *(When Data Entered)*

ACKNOWLEDGEMENTS

The US Army Materiel Systems Analysis Activity (AMSAA) recognizes the following individual for contributing to this report.

Peer Reviewer: Paul Kunselman

The author wishes to express his continued appreciation to the word processing group that labored over this manuscript and to John Kramar for his continued interest and encouragement in this work, to Dr. Frank Grubbs for his time in extended technical discussions on Lanchester models and to Toney Perkins on certain aspects of control as applied to land warfare models.

DTIC
ELECTE
MAR 1 3 1986
B

Accession For
NTIS GRA&I
DTIC TAB
Unannounced
Justification
By
Distribution
Availability
Dist
A-1

QUALITY INSPECTED 3

The next page is blank.

CONTENTS

	PAGE
ACKNOWLEDGEMENTS	iii
REFERENCES	19
APPENDIX	21
DISTRIBUTION LIST	35

The next page is blank.

STOCHASTIC ESTIMATION IN COMBINED ARMS LANCHESTER MODELING OF WARFARE

Deterministic Lanchester models of warfare with time dependent attrition coefficients has received extensive study [1]. There does not appear to be any analytical effort to incorporate observations of the battlefield into Lanchester models. This is very surprising when one considers the vast amount of effort going on in developing techniques for observing events on the battlefield and integrating intelligence in a "fusion" center. In addition, no analytical work appears to have incorporated uncertainties in the model itself. The objective of this paper is to develop a general methodology, using stochastic estimation theory as practiced in modern control theory, for predicting conditions on the battlefield from measurements or observations of the battle area that are themselves uncertain and where the parameters of the mathematical model are not known precisely. Examples are also provided to show how the general theory can be applied to two specific problems.

The fundamental Lanchester equations for homogeneous forces is given by

$$\frac{dx}{dt} = -\alpha y$$

$$\frac{dy}{dt} = -\beta x \qquad (1)$$

where x and y are the force strength of each side and α is the attrition of x force due to the weapon effectiveness of the y force and similarly β is the attrition coefficient of the y force due to the weapon effectiveness of the x force. Taking into consideration that the values α and β can change with time and also are not known exactly, we can incorporate the uncertainties in these parameters by adding to our model a gaussian white noise term in each equation so that equation (1) is modified as

$$\frac{dx}{dt} = -\alpha y + w_1(t)$$

$$\frac{dy}{dt} = -\beta x + w_2(t) \qquad (2)$$

where w_1 and w_2 are uncorrelated gaussian white noise.

Equation (2) can be written in matrix form

$$\frac{d}{dt}\begin{pmatrix} x \\ y \end{pmatrix} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix}\begin{pmatrix} x \\ y \end{pmatrix} + \begin{pmatrix} w_1(t) \\ w_2(t) \end{pmatrix}$$

or with $\underline{x} = (x, y)^T$ vector

$$\underline{A} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix} \quad \text{matrix}$$

$$\underline{w} = (w_1, w_2)^T \quad \text{vector}$$

we have

$$\frac{d\underline{x}}{dt} = \underline{A}\,\underline{x} + \underline{w} \tag{3}$$

where $\underline{w}(t)$ is gaussian white noise such that

$$E[\underline{w}(t)] = 0 \qquad \text{for all } t$$

$$\text{cov}\,[w(t), w(\tau)] = \underline{Q}\delta\ (t-\tau) \tag{3a}$$

i.e., $\underline{w} \sim N(\underline{0}, \underline{Q})$

with $\underline{Q} = \underline{Q}^T \succ 0$

Equation (3) and (3a) represents the vector form of the homogeneous Lanchester model with "plant" noise $\underline{w}$

Observation over the battlefield can be similarly characterized as

$$z_1 = c_1 x + v_1$$

$$z_2 = c_2 y + v_2$$

where z_1 is the measurement of x corrupted by measurement noise v_1, and z_2 is the measurement of y corrupted by measurement noise v_2. If we let $\underline{z} = (z_1, z_2)^T$, $\underline{x} = (x, y)^T$ and $\underline{v} = (v_1, v_2)^T$ we have

$$\underline{z} = \underline{C}\,\underline{x} + \underline{v} \tag{4}$$

with $$\underline{C} = \begin{pmatrix} c_1 & 0 \\ 0 & c_2 \end{pmatrix}$$

and $\underline{v}(t) \sim N(\underline{0}, \underline{R}(t))$ gaussion white noise

such that

$$\left.\begin{aligned} E\{\underline{v}(t)\} &= \underline{0} \quad \text{for all } t \\ \text{cov}\{\underline{v}(t), \underline{v}(\tau)\} &= \underline{R}\,\delta(t-\tau) \\ \underline{R}(t) &= \underline{R}^T(t) \succ 0 \end{aligned}\right\} \tag{4a}$$

We also require $\underline{R}$ to be non-singular i.e., $\underline{R}^{-1}$ exists.

Thus the fundamental set of equations which describe the observations over the battlefield for "stochastic" homogeneous Lanchester models of warfare is given by

$$\left.\begin{aligned} &\text{(System model):} \quad \frac{d\underline{x}(t)}{dt} = \underline{A}\,\underline{x}(t) + \underline{w}(t) \\ &\text{(Measurement model):} \quad \underline{z}(t) = \underline{C}\,\underline{x}(t) + \underline{v}(t) \end{aligned}\right\} \tag{5}$$

where the initial state $\underline{x}(t_0)$ is modeled as a random vector since the initial conditions are not precisely known. To characterize the initial state $\underline{x}(t_0)$ we need

$$\left.\begin{aligned} &E\{\underline{x}(t_0)\} = \bar{\underline{x}}_0 \\ &\text{cov}[\underline{x}(t_0), \underline{x}(t_0)] = \underline{P}_0 \quad \text{initial state covariance} \\ &\underline{P}_0 = \underline{P}_0^T \geq \underline{0} \end{aligned}\right\} \tag{6}$$

The "plant" noise $\underline{w}(t)$ is used to model external disturbances and modeling errors in $\underline{A}$. Similarly, the measurement noise $\underline{v}(t)$ is used for modeling error in $\underline{C}$.

It is also assumed that $\underline{x}(t_0)$, $\underline{w}(t)$, and $\underline{v}(t)$ are independent for all t_0, t, τ, i.e.,

$$\left.\begin{aligned} &\text{cov}[\underline{x}(t_0), \underline{w}(t)] = \underline{0} \;\forall\; t_0, t \\ &\text{cov}[\underline{x}(t_0), \underline{v}(t)] = \underline{0} \;\forall\; t_0, t \\ &\text{cov}[\underline{w}(t), \underline{v}(\tau)] = \underline{0} \;\forall\; t_0, \tau \end{aligned}\right\} \tag{7}$$

The flow diagram for equation (5) is shown in Figure 1.

Thus, the stochastic estimation problem is to find an estimate $\hat{\underline{x}}$ for the stochastic homogeneous Lanchester equation (5) subject to equations (3a), (4a), (6), and (7) such that, for a given set of past measurements $\underline{z}(1)$, $\underline{z}(2)$, ... , $\underline{z}(t)$, the estimate $\hat{\underline{x}}(t)$ minimizes

$$J = E\left\{ ||\underline{x}(t) - \hat{\underline{x}}(t)||^2 \mid \underline{z}(1), \underline{z}(2), \ldots, \underline{z}(t)\right\} \tag{7a}$$

in the least squares sense.

It is now well known that the Kalman-Bucy filter [2, 3, 4] provides such an estimate and that $\hat{\underline{x}}$ satisfies


PLANT
NOISE
W(t)
X(t0) INITIAL STATE
V(t)
MEASUREMENT
NOISE
+
TRUE STATE
X(t)
Σ
Ẋ(t)
∫
C
Σ
Z(t)
OUTPUT
+
A

Figure 1.

$$\frac{d\hat{\underline{x}}}{dt} = \underline{A}\,\hat{\underline{x}}(t) + \underline{H}\,[\underline{z}(t) - \underline{C}\,\hat{\underline{x}}(t)\,] \tag{8}$$

$$\hat{\underline{x}}\,(t_o) = \underline{\bar{x}}_o$$

where the filter gain matrix H is given by

$$H = \underline{P}(t)\,\underline{C}^T\,\underline{R}^{-1}\,(t) \tag{9}$$

with the error covariance matrix $\underline{P}(t)$ satisfies the Riccati equation

$$\frac{d\underline{P}(t)}{dt} = \underline{A}\,\underline{P}(t) + \underline{P}(t)\underline{A}^T + \underline{Q} - \underline{P}(t)\,\underline{C}^T\,\underline{R}^{-1}\,\underline{C}\,\underline{P}(t) \tag{10}$$

with $\underline{P}(t_o) = \underline{P}_o$

The Kalman-Bucy filter can be implemented as shown in Figure 2.

The state estimate $\hat{\underline{x}}$ provides a battlefield commander with a predicted estimate of the future conditions of his force strength and that of his opponents based on available information up to the present time for a homogeneous force.

The heterogeneous or combined arms Lanchester model of warfare can be simply achieved by expanding the definition of x and y to a force structure made up of several distinct weapon systems x_i, y_j for i = 1, 2, ..., n, j = 1, 2, ..., m such that

$$\underline{x} = (x_1, x_2, \ldots, x_n, y_1, y_2, \ldots, y_m)^T \qquad n + m \text{ vector}$$

and

$$\underline{w} = (w_1, w_2, \ldots, w_n, w_{n+1} \ldots w_{n+m})^T \qquad n + m \text{ vector}$$

$$\underline{v} = (v_1, v_2, \ldots, v_n, v_{n+1}, \ldots, v_{n+m})^T \qquad n + m \text{ vector}$$

$$\underline{z} = (z_1, z_2, \ldots, z_n, z_{n+1}, \ldots, z_{n+m})^T \qquad n + m \text{ vector}$$

and where the plant matrix F takes on the form

$$\underline{F} = \begin{pmatrix} \underline{0} & \underline{A} \\ \underline{B} & \underline{0} \end{pmatrix} \qquad (n + m)\ X\ (n + m) \text{ matrix}$$

where $\underline{A}$, $\underline{B}$ are now matrices which represent the attrition coefficients associated with weapon y_j and x_i for j = 1, 2, m and i = 1, 2, ... n.



Figure 2. KALMAN - BUCY Filter

Thus for the heterogenous case equation (5) is transformed into

$$\frac{d\underline{x}}{dt} = \underline{F}\,\underline{x} + \underline{w}$$
$$\underline{z}(t) = \underline{C}\,\underline{x} + \underline{v} \qquad (11)$$

Naturally, $\underline{C}$ is similarly defined. The implementation is similar to that shown in Figure 1. All the constraints imposed on $\underline{w}$ and $\underline{v}$ are the same as in the homogeneous case. The optimal estimate, generated by the Kalman-Bucy filter for the heterogeneous systems, is also satisfied for equation (8) through (10). The Kalman-Bucy filter approach can also be applied to the situation in which F(t) and C(t) are time dependent.

Discrete System

We can transform the homogeneous system (equation (5)) to discrete true model if we use

$$\frac{d\underline{x}(t)}{dt} = \lim_{\Delta t \to 0} \frac{\underline{x}(t_k) - \underline{x}(t_{K-1})}{\Delta t}$$

so that

$$\underline{x}(t_K) - \underline{x}(t_{K-1}) = \underline{A}\Delta t\ \underline{x}\ (t_{k-1}) + \Delta t\ \underline{w}\ (t_{k-1})$$
$$\underline{z}(t_k) = \underline{C}\ \underline{x}\ (t_{k-1}) + \underline{v}\ (t_{k-1})$$

which reduces to

$$\left.\begin{aligned} \underline{x}(t_k) &= \underline{\Phi}_{K-1}\ \underline{x}(t_{K-1}) + \Delta t\ \underline{w}\ (t_{K-1}) \\ \underline{z}(t_k) &= \underline{C}\ \underline{x}\ (t_K) + \underline{v}\ (t_k) \end{aligned}\right\} \qquad (12)$$

where

$$\left.\begin{aligned} \Phi_{K-1} &= \underline{I} + \underline{A}\Delta t, \\ \underline{w}_{K-1} &= \Delta t \underline{w}(t_{K-1}) \\ \underline{w}(t_k) &\sim N\ (\underline{0}, \underline{Q}_K) \\ \underline{Q}_K &= \underline{Q}(t)/\Delta t \\ v(t_k) &\sim N\ (\underline{0}, \underline{R}_K) \\ \underline{R}_K &= \underline{R}(t)/\Delta t \end{aligned}\right\} \qquad (13)$$

with initial state $\underline{x}(o)$ gaussian and $\underline{x}(o)$, $\underline{w}(t_{k-1})$, $\underline{v}\ (t_{k-1})$ are independent for all t, τ.

The optimal filtering problem is to determine $\underline{x}(t_{K-1})$ given a sequence of past measurements $\underline{z}(1)$, $\underline{z}(2)$, ..., $z(t_{K-1})$ where the optimal estimate is defined as the conditional mean

$$\text{(known)}\quad \hat{\underline{x}}\,(t_{K-1} \mid t_{K-1}) = E\left\{ \underline{x}\,(t_{K-1}) \mid \underline{z}(1), \underline{z}(2), \ldots, \underline{z}(t_{K-1}) \right\} \qquad (14)$$

where $p(\underline{x}\,(t_{K-1}) \mid \underline{z}(1), z_2(2), \ldots, \underline{z}(t_{K-1}))$, the conditional density function, is gaussian and known. The conditional covariance

$$\text{(known)}\quad \underline{P}(t_{K-1} \mid t_{K-1}) = \text{cov}\,[\underline{x}(t_{K-1}), \underline{x}(t_{K-1}) \mid \underline{z}(1), \underline{z}(2), \ldots, z(t_{K-1})] \qquad (15)$$

We are interested in predicting $\underline{x}(t_K)$ given observations $\underline{z}(1)$, $\underline{z}(2)$, ..., $\underline{z}(t_{K-1})$ <u>before</u> measurement $\underline{z}(t_K)$ is made and then to improve that estimate $\underline{x}(t_K)$ based on expanded information $z(1)$, $z(2)$, ..., $z(t_{K-1})$, $z(t_K)$ <u>after</u> we have made a measurement or observation at t_K i.e., $\underline{z}(t_k)$.

The discrete Kalman filter can be summarized as follows:

<u>State Dynamics Model</u>:

$$\underline{x}(t_K) = \underline{\Phi}_{K-1}\,\underline{x}\,(t_{K-1}) + \underline{w}\,(t_{K-1})$$

$$\underline{w}(t_K) \sim N(\underline{0}, \underline{Q}_K)$$

<u>Measurement Model</u>

$$\underline{z}(t_K) = \underline{C}\,\underline{x}\,(t_K) + \underline{v}\,(t_K)$$

$$\underline{v}(t_K) \sim N\,(\underline{0}, \underline{R}_K)$$

<u>Off-Line Calculations</u>

Initialization (t=0):

$$\underline{P}_0 = E\,[(\underline{x}(0) - \hat{\underline{x}}(0))\,(\underline{x}(0) - \hat{\underline{x}}(0))^T]$$

<u>Predict Cycle</u>:

$$\underline{P}\,(t_K \mid t_{K-1}) = \underline{\Phi}\,(t_{K-1})\,\underline{P}(t_{K-1})\,\underline{\Phi}^T(t_{K-1}) + \underline{Q}(t_{k-1})$$

<u>Update Cycle</u>:

$$\underline{P}(t_K|t_K) = \underline{P}\,(t_K|t_{K-1}) - \underline{P}\,(t_K|t_{K-1})\,\underline{C}^T\,(t_K) \bullet$$
$$[\underline{C}(t_K)\,\underline{P}\,(t_K|t_{K-1})\,\underline{C}^T(t_K) + \underline{R}(t_K)]^{-1}\,\underline{C}(t_K)\,\underline{P}(t_K|t_{K-1})$$

<u>Filter Gain Matrix</u>:

$$\underline{H}(t_K) = \underline{P}(t_K|t_K)\,\underline{C}^T(t_K)\,\underline{R}^{-1}(t_K)$$

On-Line Calculations:

Initialization: (t=0)

$$\hat{\underline{x}}(0|0) = E\{\underline{x}(0)\}$$

Predict Cycle:

$$\hat{\underline{x}}(t_K|t_{K-1}) = \underline{\Phi}_{K-1}\,\hat{\underline{x}}(t_{k-1} \mid t_{K-1})$$

Update Cycle:

$$\hat{\underline{x}}(t_K|t_K) = \hat{\underline{x}}(t_K|t_{K-1}) + \underline{H}(t_K)\{\underline{z}(t_K) - \underline{C}(t_K)\,\hat{\underline{x}}(t_K|t_{K-1})\}$$

Innovation $\underline{r}(t_K)$

System dynamics and measurement flow diagram is given in Figure 3.

The structure of discrete time Kalman filter is shown in Figure 4.



Figure 3. Discrete System Dynamics and Measurements.



Figure 4. Discrete KALMAN-BUCY Filter.

Several examples will now be considered to demonstrate the method of computation, details of which are presented in the Appendix.

Example 1: Square law with noise in only one of the state variables.

$$\dot{x} = 0x - \alpha y$$

$$\dot{y} = \beta x + 0y + 1\,w \quad \text{(noise in y only)}$$

$$z = y + v \quad \text{(observation of y only)}$$

$$\begin{pmatrix} \dot{x} \\ \dot{y} \end{pmatrix} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix}\begin{pmatrix} x \\ y \end{pmatrix} + \begin{pmatrix} 0 \\ 1 \end{pmatrix} w$$

$$z = (0 \quad 1) \begin{pmatrix} x \\ y \end{pmatrix} + v$$

$$\underline{A} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix} \qquad \underline{G} = \begin{pmatrix} 0 \\ 1 \end{pmatrix}$$

$$\underline{H} = (0 \quad 1)$$

$$E(w(t')) = 0 \qquad E(v(t)) = 0$$

$$E(w(t)\,w(t')) = q\,\delta(t-t') \qquad E(v(t)v(t')) = r\,\delta(t-t')$$

$$\underline{Q} = q \qquad \underline{R} = r$$

$$E(x \quad (0)) = 0; \qquad E(y \quad (0)) = 0$$

$$E\begin{pmatrix} x^2 & xy \\ yx & y^2 \end{pmatrix}_{t=0} = \begin{pmatrix} P_{11}(0) & P_{12}(0) \\ P_{21}(0) & P_{22}(0) \end{pmatrix} = \underline{P}(0)$$

$$\dot{\underline{P}} = \underline{A}\,\underline{P} + \underline{P}\,\underline{A}^T + \underline{G}\,\underline{Q}\,\underline{G}^T - \underline{P}\,\underline{H}^T\underline{R}^{-1}\,\underline{H}\,\underline{P} \qquad \text{(Riccati Equation)}$$

$$\underline{P} = \begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix} \qquad P_{21} = P_{12}$$

$$\dot{P}_{11} = -2\alpha P_{21} - \left(\frac{1}{r}\right) P_{21}^2 \qquad P_{11}(0) \text{ given}$$

$$\dot{P}_{12} = -\alpha P_{22} - \beta P_{11} - \left(\frac{1}{r}\right) P_{21} \; P_{22} \qquad P_{12}(0) \text{ given}$$

$$\dot{P}_{22} = -2\beta P_{12} + q - \left(\frac{1}{r}\right) P_{22}^2 \qquad P_{22}(0) \text{ given}$$

Steady State:

$$\dot{P}_{11} = \dot{P}_{12} = \dot{P}_{22} = 0$$

$$\dot{P}_{11} = 0 \Rightarrow P_{21} = 0$$

$$\dot{P}_{12} = 0 \Rightarrow 0 = -\left(\alpha + \frac{1}{r} P_{21}\right) P_{22} - \beta P_{11}$$

$$\dot{P}_{22} = 0 \Rightarrow 0 = -2\beta P_{12} + q - \frac{1}{r} P_{22}^2$$

with $P_{12} = P_{21} = 0 \Rightarrow P_{22} = (rq)^{1/2}$

$$P_{11} = -\frac{\alpha}{\beta} P_{22} = -\left(\frac{\alpha}{\beta}\right)(rq)^{1/2}$$

$$\dot{\underline{\hat{x}}} = \underline{A}\,\underline{\hat{x}} + \underline{G}\,\underline{w} + \underline{P}\,\underline{H}^T\underline{R}^{-1}\,(\underline{z} - \underline{H}\,\underline{\hat{x}}) \qquad \underline{\hat{x}}(0) = 0$$

or

$$\dot{\underline{\hat{x}}} = (\underline{A} - \underline{K}\,\underline{H})\,\underline{\hat{x}} + \underline{K}\,\underline{z} \qquad \underline{K} = \underline{P}\,\underline{H}^T\underline{R}^{-1}$$

$$\hat{x} = \begin{pmatrix} \hat{x} \\ \hat{y} \end{pmatrix}; \quad \underline{A} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix}; \quad \underline{G} = \begin{pmatrix} 0 \\ 1 \end{pmatrix} \qquad \underline{H} = (0\ 1)$$

$$\dot{\hat{x}} = -\alpha\hat{y} + \left(\frac{1}{r}\right) P_{21}(t)\,(z - \hat{y}) \qquad \text{where } \hat{x}(0) = 0$$

$$\dot{\hat{x}} = -\alpha\hat{y} \qquad \text{at steady state}$$

$$\dot{\hat{y}} = -\beta\hat{x} + \left(\frac{1}{r}\right) P_{22}(t)\,(z - \hat{y}) \qquad \hat{y}(0) = 0$$

$$= -\beta\hat{x} + \left(\frac{q}{r}\right)^{1/2} (z - \hat{y}) \qquad \text{at steady state}$$

Summarizing the results for the case where only one state variable (y) is corrupted by noise in the systems model and measurement, the general solution satisfies the equations

$$\dot{\hat{x}} = -\alpha\hat{y} + (P_{21}(t)/r)\,(z - \hat{y}) \qquad \hat{x}(0) = 0$$

$$\dot{\hat{y}} = -\beta\hat{x} + (P_{22}(t)/r)\,(z - \hat{y}) \qquad \hat{y}(0) = 0$$

while the steady state equations take the form

$$\dot{\hat{x}} = -\alpha\hat{y} \qquad \hat{x}(0) = 0$$

$$\dot{\hat{y}} = -\beta\hat{x} + \left(\frac{q}{r}\right)^{1/2} (z - \hat{y}) \qquad \hat{y}(0) = 0$$

In the next example (example 2) we consider the case where the "plant" noise and measurement noise corrupts <u>both</u> state variables as follows.

Example 2:

$$\dot{x} = 0x - \alpha y + 1\, w_1.$$

$$\dot{y} = -\beta x + 0y + 1\, w_2.$$

$$z_1 = x + v_1$$

$$z_2 = y + v_2$$

$$\underline{z} = \begin{pmatrix} z_1 \\ z_2 \end{pmatrix}$$

$$\underline{x} = \begin{pmatrix} x \\ y \end{pmatrix} \qquad \underline{F} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix}; \quad \underline{G} = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} = \underline{I}$$

$$\dot{\underline{x}} = \underline{A}\,\underline{x} + \underline{I}\,\underline{w} \qquad \underline{w} = \begin{pmatrix} w_1 \\ w_2 \end{pmatrix}$$

$$\underline{z} = \underline{I}\,\underline{x} + \underline{v} \qquad \underline{H} = \underline{I};\ \underline{v} = \begin{pmatrix} v_1 \\ v_2 \end{pmatrix}$$

$$E\,(\underline{x}(0)) = \underline{0}$$

$$E\,(\underline{x}\underline{x}^T)_{t=0} = \underline{P}(0)$$

$$E(\underline{w}) = 0;\ E\,(\underline{w}(t)\ \underline{w}(t')^T) = \underline{Q}(t)\ \delta(t-t')$$

$$\underline{Q}(t) = \begin{pmatrix} Q_{11} & Q_{12} \\ Q_{21} & Q_{21} \end{pmatrix} \text{assumed constant}$$

$$E(\underline{v}) = 0;\ E\,(\underline{v}(t)\ \underline{v}(t')^T) = \underline{R}(t)\ \delta\,(t-t');\ \underline{R}(t) = \begin{pmatrix} R_{11} & R_{12} \\ R_{21} & R_{22} \end{pmatrix}$$

$$R^{-1} = \frac{1}{|R|}\begin{pmatrix} R_{22} & -R_{12} \\ -R_{21} & R_{11} \end{pmatrix}$$

$\underline{R}$ is assumed constant

$|R| \neq 0$

$$\underline{P} = \begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix}; \qquad |R| = R_{11}\ R_{22} - R_{21}\ R_{12}$$

$$\underline{K} = \frac{1}{|R|}\begin{pmatrix} \xi_{11} & \xi_{12} \\ \xi_{21} & \xi_{22} \end{pmatrix} = \underline{P}\,\underline{H}^T\,\underline{R}^{-1}$$

where

$$\xi_{11} = P_{11}\ R_{22} - P_{12}\ R_{21}$$

$$\xi_{12} = P_{12}\ R_{11} - P_{11}\ R_{12}$$

$$\xi_{21} = P_{21}\ R_{22} - P_{22}\ R_{21}$$

$$\xi_{22} = P_{22}\ R_{11} - P_{21}\ R_{12}$$

$$P_{11} = \sqrt{\frac{Q_{11}}{R_{22}}\,|R|} \qquad \text{Steady state}$$

$$P_{22} = \sqrt{\frac{Q_{22}}{R_{11}}\,|R|} \qquad \text{Steady state}$$

$$P_{12} = P_{21} \longrightarrow 0$$

The predicted state updated by measurements at an earlier time now is given by

$$\dot{\hat{\underline{x}}} = \underline{A}\,\hat{\underline{x}} + \underline{G}\,\underline{\bar{w}} + \underline{P}\,\underline{H}^T\,\underline{R}^{-1}\,(\underline{z} - \underline{H}\,\hat{\underline{x}}) \qquad \underline{x}(0) = 0$$

or

$$\dot{\hat{\underline{x}}} = (\underline{A}-\underline{K})\,\hat{\underline{x}} + \underline{K}\,\underline{z}$$

$$\begin{pmatrix} \dot{\hat{x}} \\ \dot{\hat{y}} \end{pmatrix} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix}\begin{pmatrix} \hat{x} \\ y \end{pmatrix} + \frac{1}{|R|}\begin{pmatrix} \xi_{11} & \xi_{12} \\ \xi_{21} & \xi_{22} \end{pmatrix}\begin{pmatrix} z_1 - \hat{x} \\ z_2 - \hat{y} \end{pmatrix}$$

$$\dot{\hat{x}}\,(t) = -\alpha\,\hat{y}\,(t) + \frac{1}{|R|}\left\{\xi_{11}\,(t)\,(z_1 - \hat{x}) + \xi_{12}(t)\,(z_2 - \hat{y})\right\}$$

$$\dot{\hat{y}}\,(t) = -\beta\,\hat{x}\,(t) + \frac{1}{|R|}\left\{\xi_{21}(t)\,(z_1 - \hat{x}) + \xi_{22}(t)\,(z_2 - \hat{y})\right\}$$

where

$$\xi_{11}(t) = P_{11}(t)\,R_{22} - P_{12}(t)\,R_{21}$$

$$\xi_{12}(t) = P_{12}(t)\,R_{11} - P_{11}(t)\,R_{12}$$

$$\xi_{21}(t) = P_{21}(t)\,R_{22} - P_{22}(t)\,R_{21}$$

$$\xi_{22}(t) = P_{22}(t)\,R_{11} - P_{21}(t)\,R_{12}$$

$$\dot{\hat{x}} = \frac{-\xi_{11}(t)}{|R|}\,\hat{x} - \left(\alpha + \frac{\xi_{12}(t)}{|R|}\right)\hat{y} + \frac{\xi_{11}(t)}{|R|}\,z_1 + \frac{\xi_{12}(t)}{|R|}\,z_2$$

$$\dot{\hat{y}} = -\left(\beta + \frac{\xi_{21}(t)}{|R|}\right)\hat{x} - \frac{\xi_{22}(t)}{|R|}\,\hat{y} + \frac{\xi_{21}(t)}{|R|}\,z_1 + \frac{\xi_{22}(t)}{|R|}\,z_2$$

$$\underline{F_2}(t) = \begin{pmatrix} \dfrac{\xi_{11}(t)}{|R|} & -\left(\alpha + \dfrac{\xi_{12}(t)}{|R|}\right) \\ -\left(\beta + \dfrac{\xi_{21}(t)}{|R|}\right) & \dfrac{\xi_{22}(t)}{|R|} \end{pmatrix} = \underline{A}(t) - \underline{K}(t)$$

$$\dot{\underline{\hat{x}}} = \underline{F_2}(t)\,\underline{\hat{x}} + \underline{B}\,\underline{z}$$

$$\underline{\hat{x}} = \begin{pmatrix} \hat{x} \\ \hat{y} \end{pmatrix} ; \quad \underline{z} = \begin{pmatrix} z_1 \\ z_2 \end{pmatrix}$$

$$\underline{B} = \begin{pmatrix} \dfrac{\xi_{11}(t)}{|R|} & \dfrac{\xi_{12}(t)}{|R|} \\ \dfrac{\xi_{21}(t)}{|R|} & \dfrac{\xi_{22}(t)}{|R|} \end{pmatrix} = \underline{K}(t)$$

$$\underline{\hat{x}}(t) = \underline{\Phi}\,(t, t_0)\,\underline{\hat{x}}(t_0) + \int_{t_0}^{t} \underline{\Phi}\,(t, \tau)\,\underline{K}(\tau)\,\underline{z}(\tau)\,d\tau$$

where $\underline{\Phi}\,(t, t_0)$ satisfies the homogeneous equation

$$\dot{\underline{\Phi}}\,(t,t_0) = \underline{F_2}\,(t)\,\underline{\Phi}\,(t,t_0)$$

Accordingly we have obtained either the differential equation for which the predicted estimate $\hat{x}$ needs to satisfy or the integral solution for this estimate in terms of its transition matrix $\underline{\Phi}(t, t_0)$.

In summary, there currently exists engineering techniques from the field of modern control theory that offers the commander in the field the opportunity of predicting or forecasting conditions of the force strength on the battlefield given prior information or observation on status of battle. The approach can handle any number of different weapon systems. The methodology described in this report will be applied to recently acquired data on tank duels and will be reported in a separate report.

REFERENCES

1. Taylor, J. G., Lanchester Models of Warfare, Volumes 1 and 2, ORSA, March 1983.

2. Gelb, A., Applied Optimal Estimates, MIT Press, 1974.

3. Bryson, A. E., and Ho, Y. C., Applied Optimal Control, Ginn and Company, 1969.

4. Sage, A. P., and White, C. C., Optimum Systems Control, 2nd Edition, Prentice-Hall, Inc. (1977).

The next page is blank.

APPENDIX

The next page is blank.

APPENDIX

Detailed analysis and derivations will now be presented to demonstrate the method of computation.

Example 1: Square law with noise in only one of the state variables.

$$\dot{x} = 0x - \alpha y$$

$$\dot{y} = \beta x + 0y + 1\ w \quad \text{(noise in y only)}$$

$$z = y + v \quad \text{(observation of y only)}$$

$$\begin{pmatrix} \dot{x} \\ \dot{y} \end{pmatrix} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix} \begin{pmatrix} x \\ y \end{pmatrix} + \begin{pmatrix} 0 \\ 1 \end{pmatrix} w$$

$$z = (0 \quad 1) \begin{pmatrix} x \\ y \end{pmatrix} + v$$

$$\underline{A} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix} \qquad \underline{G} = \begin{pmatrix} 0 \\ 1 \end{pmatrix}$$

$$\underline{H} = (0 \quad 1)$$

$$E(w(t')) = 0 \qquad E(v(t)) = 0$$

$$E(w(t)\ w(t')) = q\ \delta(t-t') \qquad E(v(t)v(t')) = r\ \delta(t-t')$$

$\underline{Q} = q \qquad \underline{R} = r$

$E(x\ (0)) = 0; \qquad E(y\ (0)) = 0$

$$E\begin{pmatrix} x^2 & xy \\ yx & y^2 \end{pmatrix}_{t=0} = \begin{pmatrix} P_{11}(0) & P_{12}(0) \\ P_{21}(0) & P_{22}(0) \end{pmatrix} = \underline{P}(0)$$

$$\dot{\underline{P}} = \underline{A}\,\underline{P} + \underline{P}\,\underline{A}^T + \underline{G}\,\underline{Q}\,\underline{G}^T - \underline{P}\,\underline{H}^T\underline{R}^{-1}\,\underline{H}\,\underline{P} \qquad \text{(Riccati Equation)}$$

$$\underline{P} = \begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix} \qquad P_{21} = P_{12}$$

$$\underline{A}\,\underline{P} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix}\begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix} = \begin{pmatrix} -\alpha P_{21} & -\alpha P_{22} \\ -\beta P_{11} & -\beta P_{12} \end{pmatrix}$$

$$(\underline{A}\,\underline{P})^T = \underline{P}\,\underline{A}^T = \begin{pmatrix} -\alpha P_{21} & -\beta P_{11} \\ -\alpha P_{22} & -\beta P_{12} \end{pmatrix}$$

$$\underline{G}\,\underline{Q}\,\underline{G}^T = q\begin{pmatrix} 0 \\ 1 \end{pmatrix}\begin{pmatrix} 0 & 1 \end{pmatrix} = q\begin{pmatrix} 0 & 0 \\ 0 & 1 \end{pmatrix}$$

$$\underline{H}\,\underline{P} = (0\ 1)\begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix} = (P_{21}, P_{22})$$

$$(\underline{H}\,\underline{P})^T = \underline{P}\,\underline{H}^T = \begin{pmatrix} P_{21} \\ P_{22} \end{pmatrix}$$

$$\underline{P}\,\underline{H}^T\underline{R}^{-1}\underline{H}\,\underline{P} = \frac{1}{r}\begin{pmatrix} P_{21} \\ P_{22} \end{pmatrix}(P_{21}, P_{22}) = \frac{1}{r}\begin{pmatrix} P_{21}^2 & P_{21}P_{22} \\ P_{21}P_{22} & P_{22}^2 \end{pmatrix}$$

$$\dot{P}_{11} = -2\alpha P_{21} - \left(\frac{1}{r}\right)P_{21}^2 \qquad P_{11}(0) \text{ given}$$

$$\dot{P}_{12} = -\alpha P_{22} - \beta P_{11} - \left(\frac{1}{r}\right)P_{21}\,P_{22} \qquad P_{12}(0) \text{ given}$$

$$\dot{P}_{22} = -2\beta P_{12} + q - \left(\frac{1}{r}\right)P_{22}^2 \qquad P_{22}(0) \text{ given}$$

Steady State:

$$\dot{P}_{11} = \dot{P}_{12} = \dot{P}_{22} = 0$$

$$\dot{P}_{11} = 0 \Rightarrow P_{21} = 0$$

$$\dot{P}_{12} = 0 \Rightarrow 0 = -\left(\alpha + \frac{1}{r} P_{21}\right) P_{22} - \beta P_{11}$$

$$\dot{P}_{22} = 0 \Rightarrow 0 = -2\beta P_{12} + q - \frac{1}{r} P_{22}^2$$

with $P_{12} = P_{21} = 0 \Rightarrow P_{22} = (rq)^{1/2}$

$$P_{11} = -\frac{\alpha}{\beta} P_{22} = -\left(\frac{\alpha}{\beta}\right)(rq)^{1/2}$$

$$\dot{\underline{\hat{x}}} = \underline{A}\,\underline{\hat{x}} + \underline{G}\,\underline{w} + \underline{P}\,\underline{H}^T\underline{R}^{-1}\,(\underline{z} - \underline{H}\,\underline{\hat{x}}) \qquad \underline{\hat{x}}\,(0) = 0$$

or

$$\dot{\underline{\hat{x}}} = (\underline{A} - \underline{K}\,\underline{H})\,\underline{\hat{x}} + \underline{K}\,\underline{z} \qquad \underline{K} = \underline{P}\,\underline{H}^T\underline{R}^{-1}$$

$$\hat{x} = \begin{pmatrix} \hat{x} \\ \hat{y} \end{pmatrix} \; ; \; \underline{A} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix} \; ; \quad \underline{G} = \begin{pmatrix} 0 \\ 1 \end{pmatrix} \qquad \underline{H} = (0\ 1)$$

$$\dot{\hat{x}} = -\alpha\hat{y} + \begin{pmatrix} 1 \\ - \\ r \end{pmatrix} P_{21}(t)\,(z - \hat{y}) \qquad \text{where } \hat{x}(0) = 0$$

$$\dot{\underline{\hat{x}}} = -\alpha\hat{y} \qquad \text{at steady state}$$

$$\dot{\hat{y}} = -\beta\hat{x} + \begin{pmatrix} 1 \\ - \\ r \end{pmatrix} P_{22}(t)\,(z - \hat{y}) \qquad \hat{y}(0) = 0$$

$$= -\beta\hat{x} + \begin{pmatrix} q \\ - \\ r \end{pmatrix}^{1/2} (z - \hat{y}) \qquad \text{at steady state}$$

Summarizing the results for the case where only one state variable (y) is corrupted by noise in the systems model and measurement, the general solution satisfies the equations

$$\dot{\hat{x}} = -\alpha\hat{y} + (P_{21}(t)/r)\,(z - \hat{y}) \qquad \hat{x}(0) = 0$$

$$\dot{\hat{y}} = -\beta\hat{x} + (P_{22}(t)/r)\,(z - \hat{y}) \qquad \hat{y}(0) = 0$$

while the steady state equations take the form

$$\dot{\hat{x}} = -\alpha\hat{y} \qquad \hat{x}(0) = 0$$

$$\dot{\hat{y}} = -\beta\hat{x} + \left(\frac{q}{r}\right)^{1/2}(z - \hat{y}) \qquad \hat{y}(0) = 0$$

In the next example (example 2) we consider the case where the "plant" noise and measurement noise corrupts <u>both</u> state variables as follows.

Example 2:

$$\dot{x} = 0x - \alpha y + 1\, w_1.$$

$$\dot{y} = -\beta x + 0y + 1\, w_2.$$

$$z_1 = x + v_1$$

$$z_2 = y + v_2$$

$$\underline{z} = \begin{pmatrix} z_1 \\ z_2 \end{pmatrix}$$

$$\underline{x} = \begin{pmatrix} x \\ y \end{pmatrix} \quad ; \quad \underline{F} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix}; \quad \underline{G} = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} = \underline{I}$$

$$\dot{\underline{x}} = \underline{A}\,\underline{x} + \underline{I}\,\underline{w} \qquad \underline{w} = \begin{pmatrix} w_1 \\ w_2 \end{pmatrix}$$

$$\underline{z} = \underline{I}\,\underline{x} + \underline{v} \qquad \underline{H} = \underline{I};\ \underline{v} = \begin{pmatrix} v_1 \\ v_2 \end{pmatrix}$$

$$E\,(\underline{x}(0)) = \underline{0}$$

$$E\ (\underline{x}\underline{x}^T)_{t=0} = \underline{P}(0)$$

$$E(\underline{w}) = 0;\ E\ (\underline{w}(t)\ \underline{w}(t')^T) = \underline{Q}(t)\ \delta(t-t')$$

$$\underline{Q}(t) = \begin{pmatrix} Q_{11} & Q_{12} \\ Q_{21} & Q_{21} \end{pmatrix} \text{ assumed constant}$$

$$E(\underline{v}) = 0;\ E\ (\underline{v}(t)\ \underline{v}(t')^T) = \underline{R}(t)\ \delta\ (t-t');\ \ \underline{R}(t) = \begin{pmatrix} R_{11} & R_{12} \\ R_{21} & R_{22} \end{pmatrix}$$

$$R^{-1} = \frac{1}{|R|}\begin{pmatrix} R_{22} & -R_{12} \\ -R_{21} & R_{11} \end{pmatrix}$$

$\underline{R}$ is assumed constant

$|R| \neq 0$

$$\underline{P} = \begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix}; \qquad |R| = R_{11}\ R_{22} - R_{21}\ \ R_{12}$$

$$\underline{G}\ \underline{Q}\ \underline{G}^T = \underline{Q}$$

$$\underline{H}\ \underline{P} = \underline{P}$$

$$\underline{R}^{-1}\ \underline{P} = \frac{1}{|R|}\ \begin{pmatrix} R_{22} & -R_{12} \\ -R_{21} & R_{11} \end{pmatrix}\ \ \begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix}$$

$$= \frac{1}{|R|}\begin{pmatrix} P_{11}\ R_{22} - R_{12}\ P_{21} & R_{22}\ P_{12} - R_{12}\ P_{22} \\ P_{21}\ R_{11} - R_{21}\ P_{11} & R_{11}\ P_{22} - R_{21}\ P_{12} \end{pmatrix}$$

$$\underline{P}\,\underline{R}^{-1}\underline{P} = \frac{1}{|R|}\begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix}\begin{pmatrix} P_{11}R_{22} - R_{12}P_{21} & R_{22}P_{12} - R_{12}P_{22} \\ P_{21}R_{11} - R_{21}P_{11} & R_{11}P_{22} - R_{21}P_{12} \end{pmatrix}$$

$$= \frac{1}{|R|}\begin{pmatrix} a_{11} & a_{12} \\ a_{21} & a_{22} \end{pmatrix}$$

where

$$a_{11} = P_{11}(P_{11}R_{22} - R_{12}P_{21}) + P_{12}(P_{21}R_{11} - R_{21}P_{11})$$

$$a_{12} = P_{11}(R_{22}P_{12} - R_{12}P_{22}) + P_{12}(R_{11}P_{22} - R_{21}P_{12})$$

$$a_{21} = P_{21}(P_{11}R_{22} - R_{12}P_{21}) + P_{22}(P_{21}R_{11} - R_{21}P_{11})$$

$$a_{22} = P_{12}(R_{22}P_{12} - R_{12}P_{22}) + P_{22}(R_{11}P_{22} - R_{21}P_{12})$$

for $R_{12} = R_{21}$ and $P_{21} = P_{12}$ it follows that $a_{12} = a_{21}$.

$$\underline{K} = \underline{P}\,\underline{H}^{T}\,\underline{R}^{-1}$$

$$= \underline{P}\,\underline{R}^{-1} = \frac{1}{|R|}\begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix}\begin{pmatrix} R_{22} & -R_{12} \\ -R_{21} & R_{11} \end{pmatrix}$$

$$= \frac{1}{|R|}\begin{pmatrix} P_{11}R_{22} - P_{12}R_{21} & R_{11}P_{12} - R_{12}P_{11} \\ P_{21}R_{22} - P_{22}R_{21} & R_{11}P_{22} - P_{21}R_{12} \end{pmatrix}$$

$$= \frac{1}{|R|}\begin{pmatrix} \xi_{11} & \xi_{12} \\ \xi_{21} & \xi_{22} \end{pmatrix}$$

where

$$\xi_{11} = P_{11}\ R_{22} - P_{12}\ R_{21}$$

$$\xi_{12} = P_{12}\ R_{11} - P_{11}\ R_{12}$$

$$\xi_{21} = P_{21}\ R_{22} - P_{22}\ R_{21}$$

$$\xi_{22} = P_{22}\ R_{11} - P_{21}\ R_{12}$$

$$\underline{K}^T = \underline{R}^{-1}\,\underline{P}$$

$$\dot{\underline{P}} = \underline{A}\,\underline{P} + \underline{P}\,\underline{A}^T + \underline{G}\,\underline{Q}\,\underline{G}^T - \underline{K}\,\underline{H}\,\underline{P}$$

$$\underline{P}(0) = \underline{P}_0$$

$$\underline{K}\,\underline{H}\,\underline{P} = \underline{P}\,\underline{I}\,\underline{R}^{-1}\,\underline{I}\,\underline{P}$$

$$= \underline{P}\,\underline{R}^{-1}\,\underline{P}$$

The Riccati equation is given by

$$\dot{\underline{P}} = \begin{pmatrix} -2\alpha P_{21} + Q_{11} - \dfrac{1}{|R|}\,a_{11} & -\beta P_{11} - \alpha P_{22} + Q_{12} - \dfrac{1}{|R|}\,a_{12} \\ -\beta P_{11} - \alpha P_{22} + Q_{21} - \dfrac{1}{|R|}\,a_{21} & -\beta P_{12} - \alpha P_{22} + Q_{21} - \dfrac{1}{|R|}\,a_{22} \end{pmatrix}$$

which for steady state $\dot{\underline{P}} = 0$ and $P_{12} \longrightarrow 0$

Evaluating $\underline{P}\,\underline{R}^{-1}$ at steady state

$$\underline{R}^{-1}\,\underline{P} = \frac{1}{|R|}\begin{pmatrix} d_{11} & d_{12} \\ d_{21} & d_{22} \end{pmatrix}$$

where

$$d_{11} = R_{22}\,P_{11} - R_{12}\,P_{21}$$

$$d_{12} = R_{22}\,P_{12} - R_{12}\,P_{22}$$

$$d_{21} = R_{11}\,P_{21} - R_{21}\,P_{11}$$

$$d_{22} = P_{22}\,R_{11} - R_{21}\,P_{12}$$

$$\underline{P}\,\underline{R}^{-1}\,\underline{P} = \frac{1}{|R|}\begin{pmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{pmatrix}\begin{pmatrix} d_{11} & d_{12} \\ d_{21} & d_{12} \end{pmatrix}$$

$$= \frac{1}{|R|}\begin{pmatrix} P_{11}\,d_{11} + d_{12}\,P_{12} & P_{11}\,d_{12} + d_{22}\,P_{12} \\ P_{21}\,d_{11} + d_{21}\,P_{22} & P_{21}\,d_{12} + d_{22}\,P_{22} \end{pmatrix}$$

with $P_{12} \longrightarrow 0$ $\quad d_{11} = R_{22} P_{11}$ $\quad d_{21} = -R_{21} P_{11}$

$d_{12} = -R_{12} P_{22}$ $\quad d_{22} = R_{11} P_{22}$

at Steady state:

$$\underline{P}\,\underline{R}^{-1}\,\underline{P} = \frac{1}{|R|}\begin{pmatrix} R_{22} P_{11}^2 & -R_{12} P_{22} P_{11} \\ -R_{21} P_{11} P_{22} & R_{11} P_{22}^2 \end{pmatrix}$$

So that at steady state

$$(1)\quad 0 = -2\alpha P_{21} + Q_{11} - \frac{1}{|R|} a_{11}$$

$$(2)\quad 0 = -\beta P_{11} - \alpha P_{22} + Q_{12} - \frac{1}{|R|} a_{12}$$

$$(3)\quad 0 = -\beta P_{11} - \alpha P_{22} + Q_{21} - \frac{1}{|R|} a_{21}$$

$$(4)\quad 0 = -2\beta P_{12} + Q_{22} - \frac{1}{|R|} a_{22}$$

Steady state: $P_{12} \longrightarrow 0$

$a_{11} \longrightarrow P_{11}^2 R_{22}$

$a_{12} \longrightarrow -R_{12} P_{22} P_{11}$

$a_{21} \longrightarrow -R_{21} P_{11} P_{22}$

$a_{22} \longrightarrow R_{11} P_{22}^2$

$$(1a)\quad 0 = Q_{11} - \frac{1}{|R|} R_{22} P_{11}^2$$

$$(2a)\quad 0 = -2P_{11} - \alpha P_{22} + Q_{12} + \frac{R_{12}}{|R|} P_{11} P_{22}$$

$$(3a) \qquad 0 = -\beta P_{11} - \alpha P_{22} + Q_{21} + \frac{R_{12}}{|R|} P_{11} P_{22}$$

$$(4a) \qquad 0 = Q_{22} - \frac{1}{|R|} R_{11} P_{22}^2$$

Thus

$$P_{11}^2 = \frac{Q_{11}}{R_{22}} |R|$$

$$(1a') \quad P_{11} = \sqrt{\frac{Q_{11}}{R_{22}} |R|} \qquad \text{Steady state}$$

$$(4a') \quad P_{22} = \sqrt{\frac{Q_{22}}{R_{11}} |R|} \qquad \text{Steady state}$$

$$P_{12} = P_{21} \longrightarrow 0$$

The predicted state updated by measurements at an earlier time now is given by

$$\dot{\hat{\underline{x}}} = \underline{A}\,\hat{\underline{x}} + \underline{G}\,\overline{\underline{w}} + \underline{P}\,\underline{H}^T\,\underline{R}^{-1}\,(\underline{z} - \underline{H}\,\hat{\underline{x}}) \qquad \underline{x}(0) = 0$$

or

$$\dot{\hat{\underline{x}}} = (\underline{A}-\underline{K})\,\hat{\underline{x}} + \underline{K}\,\underline{z}$$

$$\begin{pmatrix} \dot{\hat{x}} \\ \dot{\hat{y}} \end{pmatrix} = \begin{pmatrix} 0 & -\alpha \\ -\beta & 0 \end{pmatrix} \begin{pmatrix} \hat{x} \\ \hat{y} \end{pmatrix} + \frac{1}{|R|} \begin{pmatrix} \xi_{11} & \xi_{12} \\ \xi_{21} & \xi_{22} \end{pmatrix} \begin{pmatrix} z_1 - \hat{x} \\ z_2 - \hat{y} \end{pmatrix}$$

$$\dot{\hat{x}}\,(t) = -\alpha\,\hat{y}\,(t) + \frac{1}{|R|} \left\{ \xi_{11}\,(t)\,(z_1 - \hat{x}) + \xi_{12}(t)\,(z_2 - \hat{y}) \right\}$$

$$\dot{\hat{y}}(t) = -\beta\,\hat{x}(t) + \frac{1}{|R|}\left\{\xi_{21}(t)\,(z_1 - \hat{x}) + \xi_{22}(t)\,(z_2 - \hat{y})\right\}$$

where

$$\xi_{11}(t) = P_{11}(t)\,R_{22} - P_{12}(t)\,R_{21}$$

$$\xi_{12}(t) = P_{12}(t)\,R_{11} - P_{11}(t)\,R_{12}$$

$$\xi_{21}(t) = P_{21}(t)\,R_{22} - P_{22}(t)\,R_{21}$$

$$\xi_{22}(t) = P_{22}(t)\,R_{11} - P_{21}(t)\,R_{12}$$

$$\dot{\hat{x}} = \frac{-\xi_{11}(t)}{|R|}\,\hat{x} - \left(\alpha + \frac{\xi_{12}(t)}{|R|}\right)\hat{y} + \frac{\xi_{11}(t)}{|R|}\,z_1 + \frac{\xi_{12}(t)}{|R|}\,z_2$$

$$\dot{\hat{y}} = -\left(\beta + \frac{\xi_{21}(t)}{|R|}\right)\hat{x} - \frac{\xi_{22}(t)}{|R|}\,\hat{y} + \frac{\xi_{21}(t)}{|R|}\,z_1 + \frac{\xi_{22}(t)}{|R|}\,z_2$$

$$\underline{F_2}(t) = \begin{pmatrix} \dfrac{\xi_{11}(t)}{|R|} & -\left(\alpha + \dfrac{\xi_{12}(t)}{|R|}\right) \\ -\left(\beta + \dfrac{\xi_{21}(t)}{|R|}\right) & \dfrac{\xi_{22}(t)}{|R|} \end{pmatrix} = \underline{A}(t) - \underline{K}(t)$$

$$\dot{\underline{\hat{x}}} = \underline{F_2}(t)\,\underline{\hat{x}} + \underline{B}\,\underline{z}$$

$$\underline{\hat{x}} = \begin{pmatrix} \hat{x} \\ \hat{y} \end{pmatrix};\ \underline{z} = \begin{pmatrix} z_1 \\ z_2 \end{pmatrix}$$

$$\underline{B} = \begin{pmatrix} \dfrac{\xi_{11}(t)}{|R|} & \dfrac{\xi_{12}(t)}{|R|} \\ \dfrac{\xi_{21}(t)}{|R|} & \dfrac{\xi_{22}(t)}{|R|} \end{pmatrix} = \underline{K}(t)$$

$$\underline{\hat{x}}(t) = \underline{\Phi}\ (t,\ t_0)\ \underline{\hat{x}}(t_0) + \int_{t_0}^{t} \underline{\Phi}\ (t,\ \tau)\ \underline{K}(\tau)\ \underline{z}(\tau)\ d\tau$$

where $\underline{\Phi}\ (t,\ t_0)$ satisfies the homogeneous equation

$$\dot{\underline{\Phi}}\ (t,t_0) = \underline{F_2}\ (t)\ \underline{\Phi}\ (t,t_0)$$

Accordingly we have obtained either the differential equation for which the predicted estimate $\hat{x}$ needs to satisfy or the integral solution for this estimate in terms of its transition matrix $\underline{\Phi}\ (t,\ t_0)$.

The next page is blank.

DISTRIBUTION LIST

No. of Copies	Organization
12	Commander Defense Technical Information Center ATTN: DTIC-DDAC Cameron Station, Bldg 5 Alexandria, VA 22304-6145
2	Commander US Army Materiel Command ATTN: AMXPA AMCDMA-M 5001 Eisenhower Avenue Alexandria, VA 22333-0001
1	Director Combat Data Information Center AFWAL/FIES/CDIC Wright-Patterson AFB OH 45433-5000
1	Pentagon Library ATTN: AN-AL-RS (Army Studies) Pentagon, Room 1A518 Wash, DC 20310
1	Commander US Army Concepts Analysis Agency ATTN: CSCA-MSI-L 8120 Woodmont Avenue Bethesda, MD 20814-2797
2	General Dynamics Land Systems Division ATTN: Mr. Parker/Mr. J. O'Rourke P.O. Box 1800 Warren, MI 48090

No. of Copies	Organization
2	Commander US Army Development and Employment Agency ATTN: MODE-TED-SAB (2 cys) Ft. Lewis, WA 98433-5000
4	Director US Army TRADOC Systems Analysis Activity ATTN: ATOR-TSL ATOR-T ATOR-TE ATOR-TF White Sands Missile Range NM 88002-5502
1	Commandant US Army Infantry School ATTN: ATSH-CD-CS-OR Fort Benning, GA 31905-5400
3	Commander US Army Tank-Automotive Command ATTN: AMSTA-Z (Tech Lib) AMSTA-ZE AMSTA-ZSA Warren, MI 48090
1	HQDA (DACS-DV) Washington, DC 20310
2	Project Manager M1E1 Tank System ATTN: AMCPM-M1E1 Warren, MI 48090

DISTRIBUTION LIST (continued)

No. of Copies	Organization

Aberdeen Proving Ground

1 Dir, BRL
ATTN: AMXBR-OD-ST
Bldg 305
Aberdeen Proving Ground, MD
21005-5066

2 Dir, BRL, Bldg 328
ATTN: AMXBR-OD
AMXBR-SECAD (Dr. Jonnson/
Dr. Wolfe)
Aberdeen Proving Ground, MD
21005-5066

7 Director, AMSAA
ATTN: AMXSY-G
AMXSY-GA (W. Brooks/
E. Christman/B. Siegel/
R. Conroy)
AMXSY-GB (B. Blankenbiller)
AMXSY-C (H. Burke)
APG, MD 21005-5071

GIST

AMSAA

TITLE

BRIEFING ____ REPORT X



THE PRINCIPAL FINDINGS and recommendations of the work reported herein are as follows:

Combined Arms Lanchester Modeling of Warfare can be enhanced by using techniques of modern control theory to afford battlefield commanders improved forecast of battle.

THE MAIN ASSUMPTIONS on which the work reported herein rests are as follows:

Linear model of warfare corrupted by gaussian white noise with measurement noise constrained to gaussain white noise.

THE PRINCIPAL LIMITATIONS of this work which may affect the findings are as follows:

Need reasonable estimates of initial conditions and properties of noise corrupting both math model and measurements of battle.

THE SCOPE OF THE STUDY

Applicable to wide range of land warfare models including combined arms.

AMSAA Form 43R (18 Jul 85)
Previous ecitions of this form are obsolete.

THE STUDY OBJECTIVE

Enhance appreciation that modern control can play a key role in modeling land warfare.

THE BASIC APPROACH

Math modeling using Kalman-Bucy filtering of control theory.

THE REASONS FOR PERFORMING THE STUDY

Call attention to the fact that modern control theory provides and improved capability to provide forecasts of status of battle.

STUDY IMPACT STATEMENT (Actual or expected changes in operations realized from implementation of study results -- if possible state in quantitative terms.) May provide improved estimates of status of battle.

THE STUDY SPONSOR

N/A

ADDRESS FOR COMMENTS AND QUESTIONS

DTIC/DLSIE ACCESSION NUMBER OF FINAL REPORT

GIST

TITLE

BRIEFING ____ REPORT X

THE PRINCIPAL FINDINGS and recommendations of the work reported herein are as follows:

Combined Arms Lanchester Modeling of Warfare can be enhanced by using techniques of modern control theory to afford battlefield commanders improved forecast of battle.

THE MAIN ASSUMPTIONS on which the work reported herein rests are as follows:

Linear model of warfare corrupted by gaussian white noise with measurement noise constrained to gaussain white noise.

THE PRINCIPAL LIMITATIONS of this work which may affect the findings are as follows:

Need reasonable estimates of initial conditions and properties of noise corrupting both math model and measurements of battle.

THE SCOPE OF THE STUDY

Applicable to wide range of land warfare models including combined arms.

THE STUDY OBJECTIVE

Enhance appreciation that modern control can play a key role in modeling land warfare.

THE BASIC APPROACH

Math modeling using Kalman-Bucy filtering of control theory.

THE REASONS FOR PERFORMING THE STUDY

Call attention to the fact that modern control theory provides and improved capability to provide forecasts of status of battle.

STUDY IMPACT STATEMENT (Actual or expected changes in operations realized from implementation of study results -- if possible state in quantitative terms.)

May provide improved estimates of status of battle.

THE STUDY SPONSOR

N/A

ADDRESS FOR COMMENTS AND QUESTIONS

DTIC/DLSIE ACCESSION NUMBER OF FINAL REPORT

GIST

AMSAA	TITLE BRIEFING ____ REPORT X	

THE PRINCIPAL FINDINGS and recommendations of the work reported herein are as follows:

Combined Arms Lanchester Modeling of Warfare can be enhanced by using techniques of modern control theory to afford battlefield commanders improved forecast of battle.

THE MAIN ASSUMPTIONS on which the work reported herein rests are as follows:

Linear model of warfare corrupted by gaussian white noise with measurement noise constrained to gaussain white noise.

THE PRINCIPAL LIMITATIONS of this work which may affect the findings are as follows:

Need reasonable estimates of initial conditions and properties of noise corrupting both math model and measurements of battle.

THE SCOPE OF THE STUDY

Applicable to wide range of land warfare models including combined arms.

THE STUDY OBJECTIVE

Enhance appreciation that modern control can play a key role in modeling land warfare.

THE BASIC APPROACH

Math modeling using Kalman-Bucy filtering of control theory.

THE REASONS FOR PERFORMING THE STUDY

Call attention to the fact that modern control theory provides and improved capability to provide forecasts of status of battle.

STUDY IMPACT STATEMENT (Actual or expected changes in operations realized from implementation of study results -- if possible state in quantitative terms.) May provide improved estimates of status of battle.

THE STUDY SPONSOR

N/A

ADDRESS FOR COMMENTS AND QUESTIONS

DTIC/DLSIE ACCESSION NUMBER OF FINAL REPORT

GIST

AMSAA

TITLE

BRIEFING ____ REPORT X

THE PRINCIPAL FINDINGS and recommendations of the work reported herein are as follows:

Combined Arms Lanchester Modeling of Warfare can be enhanced by using techniques of modern control theory to afford battlefield commanders improved forecast of battle.

THE MAIN ASSUMPTIONS on which the work reported herein rests are as follows:

Linear model of warfare corrupted by gaussian white noise with measurement noise constrained to gaussain white noise.

THE PRINCIPAL LIMITATIONS of this work which may affect the findings are as follows:

Need reasonable estimates of initial conditions and properties of noise corrupting both math model and measurements of battle.

THE SCOPE OF THE STUDY

Applicable to wide range of land warfare models including combined arms.

THE STUDY OBJECTIVE

Enhance appreciation that modern control can play a key role in modeling land warfare.

THE BASIC APPROACH

Math modeling using Kalman-Bucy filtering of control theory.

THE REASONS FOR PERFORMING THE STUDY

Call attention to the fact that modern control theory provides and improved capability to provide forecasts of status of battle.

STUDY IMPACT STATEMENT (Actual or expected changes in operations realized from implementation of study results -- if possible state in quantitative terms.) May provide improved estimates of status of battle.

THE STUDY SPONSOR

N/A

ADDRESS FOR COMMENTS AND QUESTIONS

DTIC/DLSIE ACCESSION NUMBER OF FINAL REPORT

GIST

AMSAA

TITLE

BRIEFING ____ REPORT X



THE PRINCIPAL FINDINGS and recommendations of the work reported herein are as follows:

Combined Arms Lanchester Modeling of Warfare can be enhanced by using techniques of modern control theory to afford battlefield commanders improved forecast of battle.

THE MAIN ASSUMPTIONS on which the work reported herein rests are as follows:

Linear model of warfare corrupted by gaussian white noise with measurement noise constrained to gaussain white noise.

THE PRINCIPAL LIMITATIONS of this work which may affect the findings are as follows:

Need reasonable estimates of initial conditions and properties of noise corrupting both math model and measurements of battle.

THE SCOPE OF THE STUDY

Applicable to wide range of land warfare models including combined arms.

AMSAA Form 43R (18 Jul 85)
Previous editions of this form are obsolete.

THE STUDY OBJECTIVE

Enhance appreciation that modern control can play a key role in modeling land warfare.

THE BASIC APPROACH

Math modeling using Kalman-Bucy filtering of control theory.

THE REASONS FOR PERFORMING THE STUDY

Call attention to the fact that modern control theory provides and improved capability to provide forecasts of status of battle.

STUDY IMPACT STATEMENT (Actual or expected changes in operations realized from implementation of study results -- if possible state in quantitative terms.) May provide improved estimates of status of battle.

THE STUDY SPONSOR

N/A

ADDRESS FOR COMMENTS AND QUESTIONS

DTIC/DLSIE ACCESSION NUMBER OF FINAL REPORT

GIST

AMSAA	TITLE BRIEFING ____ REPORT X	

THE PRINCIPAL FINDINGS and recommendations of the work reported herein are as follows:

Combined Arms Lanchester Modeling of Warfare can be enhanced by using techniques of modern control theory to afford battlefield commanders improved forecast of battle.

THE MAIN ASSUMPTIONS on which the work reported herein rests are as follows:

Linear model of warfare corrupted by gaussian white noise with measurement noise constrained to gaussain white noise.

THE PRINCIPAL LIMITATIONS of this work which may affect the findings are as follows:

Need reasonable estimates of initial conditions and properties of noise corrupting both math model and measurements of battle.

THE SCOPE OF THE STUDY

Applicable to wide range of land warfare models including combined arms.

THE STUDY OBJECTIVE

Enhance appreciation that modern control can play a key role in modeling land warfare.

THE BASIC APPROACH

Math modeling using Kalman-Bucy filtering of control theory.

THE REASONS FOR PERFORMING THE STUDY

Call attention to the fact that modern control theory provides and improved capability to provide forecasts of status of battle.

STUDY IMPACT STATEMENT (Actual or expected changes in operations realized from implementation of study results -- if possible state in quantitative terms.)

May provide improved estimates of status of battle.

THE STUDY SPONSOR

N/A

ADDRESS FOR COMMENTS AND QUESTIONS

DTIC/DLSIE ACCESSION NUMBER OF FINAL REPORT

DTIC

END

4-86